

PMTBaseERD Supplement (ver 0.00b)

Errata

Corrections are shown in yellow.

S2.2.2.2 Value tolerances

The values in the Table shall be achieved as closely as possible using standard value resistors with a tolerance of 5% or better.

Note: F2 and Dy1 are at equal potential. F1 and F3 are at equal potential between the potential of Dy1 and the potential of Dy2.

Table S2.1 Relative bleeder chain resistance values

Interval	Relative value
K - Dy1	22.6
Dy1 - F1	0.6
F1 - Dy2	3.4
Dy2 - Dy3	5
Dy3 - Dy4	3.33
Dy4 - Dy5	1.67
Dy5 - Dy6	1
Dy6 - Dy7	1.2
Dy7 - Dy8	1.5
Dy8 - Dy9	2.2
Dy9 - Dy10	3
Dy10 - A	2.4